



*BZ Switches*

## WOYR2.E12252 Switches, Special Use - Component

[Page Bottom](#)

[Print-friendly version](#)

[Questions?](#)

[Previous Page](#)

### Switches, Special Use - Component

See General Information for Switches, Special Use - Component

**HONEYWELL SENSING & CONTROL, DIV  
OF HONEYWELL INC**  
11 W SPRING ST  
FREEPORT, IL 61032 USA

E12252

Cat. No.	Electrical Rating Code
AML21, f/b B, C, E, F, G, H, J, K, L, M, N, P, R or S, f/b B, G or W, f/b A, B, C or E, f/b 2 or 3, f/b A, B, C or E, f/b A thru D, ww/o letters and/or numbers, f/b L173 or L203.	L173 or L203
AML21B100, -B101, -C100 thru -C105, -E100, -E101, -E102, -G100, -G101 and -G102, f/b L173.	L173
AML21BBA2CD-001 f/b L173 and L203.	L173 and L203
AML22 f/b C, H, J, K, L or M, f/b B, G, or W, f/b B, C, D, E, F, H, J, K, L, M, R, S, T, W or X, f/b 2, 3, 8 or 9, f/b A thru E, f/b A thru D, ww/o letters and/or numbers,	L173 or L203

A, B, D, L, M, N, Q, S, T, V	or L268
or W, ww/o numbers, ww/o A, AR, B,	
D or P with numerals, f/b	
L101, L161, L167, L174 or L268.	
BM, WM, YM, ww/o D, E, EG, F, G	L82, L167
H, T, V or V6, ww/o 1, f/b A, B, D, E	
L, M, N, P, Q, R, S, W, X or a	
combination of these letters	
ww/o numbers, w/wo A, AR, B, D, P, PC,	
ww/o numbers, f/b L82 or L167.	
B, <del>BZ</del> , G, R, WZ or YZ, ww/o D, E,	L8, L35, L96 or L233.
E6, F, G1, G2, H1, H2, T, V or	
V6, ww/o -1 or -2, f/b D, E, F,	
L, M, N, Q, R, S, T, W or X, or	
a combination of these letters,	
ww/o numerals, ww/o hyphenated	
letter A, B, D, K, P, PC, PP or	
T, or TC without a hyphen, ww/o	
numerals, ww/o -S, ww/o BP, C,	
D, F, JH, P, R, RNC, RNO, S or	
WP, ww/o numerals, f/b L8, L35,	
L96, or L233.	
B, BZ, G, R, WZ or YZ ww/o D, E,	L9 or L233
E6, F, G1, G2, H1, H2, T, V or	
V6, ww/o -1, -2, -3 or -7, f/b	
D, L, M, N, Q, S, T, W or X, or	
combination of these letters,	
ww/o numerals, ww/o hyphenated	
letter A, B, D, K, P, PC, PP or	
T or TC without a hyphen, ww/o	

numerals, ww/o -S, ww/o BP, C,	
D, F, JH, P, R, RNC, RNO, S or	
WP, f/b L9 or L233	
B, BZ, G, R, WZ or YZ, ww/o D, E,	L22 or
E6, F, G1, G2, H1, H2, T, V	L279
or V6, w/wo -1, -2, -3 or -7,	
f/b D, L, M, N, Q, R, S, T or	
W, or a combination of these	
letters, ww/o numerals, ww/o	
hyphenated letter A, B, D, K,	
P, PC or PP, or T without a	
hyphen, ww/o numerals; ww/o	
-S, f/b L22 or L279.	
B, BZ, G, R, WZ or YZ ww/o D, E,	L67 or L144
E6, F, G1, G2, H1, H2, T, V	
or V6, f/b hyphenated letter	
D, L, M, N, Q, R, S, T, W or	
X, or a combination of these	
letters, ww/o numerals, ww/o	
hyphenated letter A, B, D, K,	
P, PC, PP or T, or TC without	
a hyphen, ww/o numerals, ww/o	
-S, f/b L67 or L144. (Note:	
The letter X may appear	
anywhere after the first	
hyphen)	
B, BZ, G, R, WZ or YZ, ww/o D, E, E6,	L95 or L169
F, G1, G2, H1, H2, T, V or V6, ww/o	
-1, -2, -3 or -7, f/b D, L, M, N, Q, R,	
S, T or W, or a combination of these letters,	

ww/o numerals, ww/o hyphenated letter A, B, D, K, P, PC or PP, or T without a hyphen, ww/o numerals, ww/o -S, f/b L95 or L169.	
B, BZ, G, R, WZ or YZ ww/o D, E, E6, F, G1, G2, H1, H2, T, V or V6, f/b -1, -2, -3, or -7, f/b D, L, M, N, Q, R, S, T, W or X, or a combination of these letters, ww/o numerals, ww/o hyphenated letter A, B, D, K, P, PC, PP or T, or TC without a hyphen, ww/o numerals, ww/o -S, ww/o BP, C, D, F, JH, P, R, RNC, RNO or S, ww/ numerals, f/b L96 or L233	L96 or L233
B, BZ, G, R, WZ or YZ ww/o D, E, E6, F, G1, G2, H1, H2, T, V or V6, f/b -1, -2 or -3, f/b D, L, M, N, Q, R, S, T or W, or a combination of these letters, ww/o numerals, ww/o hyphenated letter A, B, D, K, P, PC or PP, or T without a hyphen, ww/o numerals, ww/o -S, ww/o BP, C, D, F, JH, P, R, RNC, RNO or S, ww/o numerals, f/b L103 or L233	L103 or L233
BZ ww/o D, E, E6, F, G1, G2, H1, H2, T, V or V6, f/b -2F or -2G, ww/o D, L, M, N, Q, S, T or W, or a combination of these letters, ww/o numerals, ww/o hyphenated letter A, B, D, K, P, PC or PP, or T without a hyphen, ww/o numerals, ww/o -S, f/b L9	L9
BZ-R241 or BZ-R2418-A2 f/b L4	L4

BZ-R814-PP1-L189	L189
BZ-RW843515 or BZ-R214	L169
f/b L169	
BZ, WZ or YZ ww/o D, E, E6, F, G1, G2, H1, H2, T, V or V6, f/b -Y, -2Y, -3Y or -7Y, f/b D, K, L, M, N, Q, S, T, W or X or a combination of these letters, ww/o numerals, f/b hyphenated letter A, B, D, K, P, PC, PP or T or TC without a hyphen, ww/o numerals, f/b L4 or L121	L4 or L121
BZ, WZ or YZ ww/o D, E, E6, F, G1, G2, H1, H2, T, V or V6, ww/o -1, -2, -3 or -7, f/b D, L, M, N, Q, S, T, or W, or a combination of these letters, ww/o numerals, ww/o hyphenated letter A, B, D, K, P, PC, PP or T, without a hyphen, ww/o numerals, ww/o -S, f/b L4, L34 or L130	L4, L34 or L130
BZ, WZ or YZ ww/o D, E, E6, F, G1, G2, H1, H2, T, V or V6, f/b -2, -3 or -7, f/b D, L, M, N, Q, R, S, T, W or X, or a combination of these letters, ww/o numerals, ww/o hyphenated letter A, B,	L35

D, K, P, PC or PP or T, without a hyphen, ww/o numerals, ww/o -S, f/b L35	
BZ, WZ or YZ ww/o D, E, E6, F, G1, G2, H1, H2, T, V or V6, f/b hyphenated letter D, E, L, M, N, Q, R, S, T or W, or a combination of these letters, ww/o numerals, ww/o hyphenated letter A, B, D, K, P, PC, or T, or TC without a hyphen, ww/o numerals, ww/o -S, f/b L65 L96, L103, L111 or L147	L65, L96, L103, L111 or L147
BZ, WZ or YZ ww/o D, E, E6, F, G1, G2, H1, H2, T, V or V6, f/b -2A or -3A, f/b D, L, M, N, Q, S, T or W, or a combination of these letters, ww/o numerals, ww/o hyphenated letter A, B, D, K, P, PC, PP, or T without a hyphen, ww/o numerals, ww/o -S, f/b L73 or L180	L73 or L180
BZ, WZ or YZ ww/o D, E, E6, F, G1, G2, H1, H2, T, V or V6, f/b -2, -3 or -7, f/b D, L, M, N, Q, R, S, T or W, or a combination of these letters, ww/o numerals, ww/o hyphenated	L74, L270 or L271

letter A, B, D, K, P, PC or	
PP, or T without a hyphen,	
ww/o numerals, ww/o -S, f/b	
L74, L270 or L271	
BZ, WZ or YZ f/b -2, f/b D, L, M,	L87
N, Q, R, S, T or W, or a	
combination of these letters,	
ww/o numerals, ww/o hyphenated	
letter A, B, D, K, P, PC or	
PP, or T without a hyphen,	
ww/o numerals, ww/o -S, f/b	
L87	
BZ, WZ or YZ ww/o D, E, E6, F, G1,	L197 or L233
G2, H1, H2, T, V or V6, f/b	
-7, f/b D, L, M, N, Q, R, S,	
T or W, or a combination of	
these letters, ww/o numerals,	
ww/o hyphenated letter A, B,	
D, K, P, PC or PP, or T without	
a hyphen, ww/o numerals, ww/o	
-S, f/b L197 or L233	
BZ, WZ or YZ ww/o D, E, E6, T, V	L148
or V6, f/b -1 or -2, f/b D, L,	
M, N, Q, R, S, T, W or X, or a	
combination of these letters,	
ww/o numerals, ww/o hyphenated	
letter A, B, D, K, P, PC or	
PP, or T without a hyphen, ww/o	
numerals, ww/o -S, f/b L148	
DC, DO, or DT, ww/o D, E, E6, F2,	L59 or L120

G1, G2, H1, H2, T, V or V6, f/b -2R or -3R, ww/o D, L, M, N, Q, S, T or V, ww/o numerals, ww/o -A, -B, -D or -PC, ww/o -LH or -RH with numerals, f/b L59 or L120	
G-(Refer to BZ Series for details)	—
MC, MO or MT ww/o suffix D, E, E6,	L20, L168 or L210
F, G1, G2, H1, H2, T, V or V6, f/b -4R, ww/o letter B, L, Q, N, S or V, ww/o numerals, ww/o additional letters A, B, D or P, with numerals, f/b L20, L168 or L210	
MML21 f/b E, B, K or H, f/b A, K, L, M, N, P or W, f/b 2 or 3, f/b AA thru AD, f/b A, K, L or W, ww/o GH, GS, RH, RS, XX, YH or YS, ww/o DG, DR, DY, LB, LG, LK, LR, LW or LY, ww/o 20, ww/o -000 thru -999, f/b L22	L22
MML21 f/b E, B, K or H, f/b A, K, L, M, N, P or W, f/b 2 or 3, f/b BA thru BD, f/b A, K, L or W, ww/o GH, GS, RH, RS, XX, YH or YS, ww/o DG, DR, DY, LB, LG, LK, LR, LW or LY ww/o 20, ww/o -000 thru -999, f/b L222	L222
MML21LC f/b 2, 2DG, 2DR, 2DY, 2LB, 2LG, 2LR, 2LW, 2LY, 2RA, DG, DR,	L222



16SBBN, HRN91-26SBBNHRN91-14SBBN, HRN91-24SBBN, HRN91-13SBBN, HRN91-23SBBNHRN91-18SBBN, HRN91-28SBBN, HRN91-11SBBN, HRN91-21SBBNHRN91-15SBBN, HRN91-25SBBN, HRN91-17SBBN, HRN91-27SBBNHRL91-22BRNB,				
HRL91-23DRRB, HRL91-21DRRB, HRL91-27DRRBHRL91-22GGAB, HRL91-23UGGB, HRL91-21UGGB, HRL91-22UGGBSRN91-12SBBN,				
SRN91-22SBBN, SRN91-16SBBN, SRN91-26SBBNSRN91-14SBBN, SRN91-24SBBN, SRN91-13SBBN, SRN91-23SBBNSRN91-18SBBN, SRN91-28SBBN, SRN91-11SBBN, SRN91-21SBBNSRN91-15SBBN, SRN91-25SBBN, SRN91-17SBBN, SRN91-27SBBNSRL91-22BRNB,				
SRL91-23DRRB, SRL91-21DRRB, SRL91-27DRRB, SRL91-22GGAB, SRL91-23UGGB, SRL91-21UGGB, SRL91-22UGGB				
MRS Series				
MRN Series				
MRL Series				
<b>Code</b>	<b>Electrical Rating</b>	<b>Code</b>	<b>Electrical Rating</b>	
L1	15A, 125-250*-480V, ac	L13	10A, 125V, ac;	
L2	15A, 125-250*-480Vac;		5A, 250*V, ac.	
	0.5, 125V, dc;	L15	15A, 125-250*-480V, ac;	
	0.25A, 250V, dc.		10A, 125V, ac "L";	
L4	5A, 250*Vac		3/4hp, 125V, ac;	
			1-1/2hp, 250*V, ac;	
L7	7A, 250*V, ac		0.5A, 125V, DC;	
L8	10A, 125-250*-480V, ac		0.25A, 250V, DC.	
L9	10A, 125-250*-480V, ac;	L17	20A, 125-250*-480V, ac;	
	0.5A, 125V, DC;		3/4hp, 125V, ac;	
	0.25A, 250V, DC.		1-1/2hp, 250*V, ac.	
L10	10A, 125-250*Vac;			

	0.5A, 125V dc;		
	0.25A, 250V dc.		
L19	15A, 125-250*-480V, ac;	L25	10A, 125-250*V, ac;
	3/4hp, 125V, ac;		1/2hp, 125V, ac.
	1-1/2hp, 250V, ac;	L29	10A, 250*V, ac.
	0.5A, 125V, DC;	L33	20A, 125-250*-480V, ac;
	0.25A, 250V, DC.		1hp, 125v, ac;
L20	10A, 125V, ac-DC;		2hp, 250*V, ac;
	1/8hp, 125V, ac-DC.		0.3A, 125V, DC;
L22	1A, 125V, ac.		0.15A, 250V, DC.
L23	20A, 125-250*-480V, ac;	L34	5A, 125-250*-480V,ac.
	10A, 125V, ac "L";	L35	5A, 125-250*-480V, ac;
	0.5A, 125V, DC;		0.5A, 125V, DC;
	0.25A, 250V, DC;		0.25A, 250V, DC.
	1hp, 125V, ac;		
	2hp, 250*V, ac.		
L50	17A, 125-250*-480V, ac;	L58	25A, 125-250*-480V, ac;
	1hp, 125V, ac;		3/4hp, 125V, ac;
	2hp, 250*V, ac;		1-1/2hp, 250*V, ac;
	10A, 125V, ac "L"		1A, 125V, DC;
	0.5A, 125V, DC;		0.5A, 250V, DC.
	0.25A, 250V, DC.	L59	10A, 125-250*V, ac;
L54	15A, 125-250*V, ac;		0.3A, 125V, DC;
	1/3hp, 125V, ac;		0.15A, 250V, DC.
	3/4hp, 250*V, ac;	L62	15A, 125-250*V, ac;
	0.5A, 125V, DC;		3/4hp, 125V, ac;
	0.25A, 250V, DC.		1-1/2hp, 250*V, ac.
L55	15A, 125-250*V, ac;	L65	15A, 125-250*-480V ac;
	1/2hp, 125V, ac;		1/2hp, 125V, ac;
	1hp, 250*V, ac;		1hp, 250*V, ac.

	0.5A, 125V, DC;		
	0.25A, 250V, DC.		
L67	15A, 125-250*-480V, ac;	L81	22A, 125-250*-277Vac;
	1/2hp, 250*V, ac;		3/4hp, 125Vac;
	1/4hp, 125V, ac;		1-1/2hp, 250Vac.
	0.5A, 125V, DC;	L82	22A, 125-250*-277V, ac;
	0.25A, 250V, DC.		1/2hp, 250*Vac;
L73	15A, 125-250*-480V, ac;		1/4hp, 125Vac.
	1/4hp, 125V, ac;	L83	15.1A, 1/2hp, 125-250*V, ac;
	1/2hp, 250*V, ac;		0.5A, 125V, DC;
	1A, 125V, DC;		0.25A, 250V, DC;
	0.5A, 250V, DC.		5A, 125V, ac "L".
L74	15A, 125-250*-480V, ac;	L84	15A, 125-250*-480V, ac;
	2A, 600V, ac;		1/2hp, 125V, ac;
	1/8hp, 125V, ac;		1hp, 250*V, ac;
	1/4hp, 250*V, ac;		0.5A, 125V, DC;
	0.5A, 125V, DC;		0.25A, 250V, DC.
	0.25A, 250V, DC.		
L85	10A, 125-250*-480V, ac;	L93	10A, 125-250*V, ac;
	1/8hp, 125V, ac;		1/3hp, 125-250*V, ac.
	1/4hp, 250*V, ac.	L95	10A, 125-250*-480Vac;
L86	15.1A, 125-250*V, ac;		1/8hp, 125Vac;
	1/3hp, 125-250V, ac;		1/4hp, 250Vac,
	0.5A, 125V, DC;	L96	15A, 125-250*-480V,ac;
	0.25A, 250V, DC;		1/8hp, 125V, ac;
	5A, 125V, ac "L".		1/4hp, 250*V, ac;
L87	15A, 125-250*-480V, ac;		0.5A, 125V, DC;
	1/4hp, 125-250*V, ac;		0.25A, 250V, DC.
	0.5A, 125V, DC;	L97	20A, 125-250*-480V, ac;
	0.25A, 250V, DC.		10A, 125V, ac "L";

L88	15A, 125-250*-480V, ac;		0.5A, 125V, DC;
	1/3hp, 125-250*V, ac;		0.25A, 250V, DC;
	0.5A, 125V, DC;		1-1/2hp, 125V, ac;
	0.25A, 250V, DC.		2hp, 250*V, ac.
L98	10A, 125-250*-480V, ac;	L102	22A, 125-250*-480V, ac;
	1/2hp, 125V, ac;		1/4hp, 125V, ac;
	1hp, 250*V, ac;		1/2hp, 250V, ac.
	0.8A, 125V, DC;	L103	15A, 125-250*-480V, ac;
	0.4A, 250V, DC.		1/8hp, 125V, ac;
L99	10A, 1/4hp,		1/4hp, 250*V, ac.
	125-250*V, ac.	L104	22A, 125-250*-480V, ac;
L100	10A, 125-250*-480V, ac;		3/4hp, 125V, ac;
	1/2hp, 125V, ac;		2hp, 250*V, ac.
	1hp, 250*V, ac.	L109	5A, 1/10hp, 125-250*V, ac.
L101	22A, 125-250*-480V, ac;	L110	3A, 1/6hp, 250*V, ac;
	1/4hp, 125V, ac;		3A, 1/10hp, 125V, ac.
	1/2hp, 250*V, ac;	L111	15A, 125-250*-277V, ac;
	0.5A, 125V, DC;		1/8hp, 125V, ac;
	0.25A, 250V, DC.		1/4hp, 250*V, ac.
L112	10A, 1/3hp, 125-250*V, ac;	L119	3A, 250*V, ac.
	0.5A, 125V, DC;	L120	10A, 125-250*V, ac;
	0.25A, 250V, DC;		1/10hp, 125V, ac;
	4A, 125V, ac "L".		1/8hp, 250V, ac;
L113	15.1A, 1/2hp, 125-250*V, ac;		0.3A, 125V, DC;
	5A, 125V, ac "L".		0.15A, 250V, DC.
L115	10A, 125-250*V, ac;	L121	5A, 250*V, ac;
	1/3hp, 125V, ac;		1/6hp, 125V, ac.
	3/4hp, 250*V, ac;	L122	3A, 250*V, ac.
	0.5A, 125V, DC;	L123	7A, 125-250*V, ac;
	0.25A, 250V, DC.		1/4hp, 125-250*V, ac.

L116	10A, 1/3hp, 125-250*V, ac;	L126	10A, 125-250*-480V, ac;
	4A, 125V, ac "L".		1/3hp, 125V, ac;
L117	5A, 125V, ac.		3/4hp, 250*V, ac;
L118	10A, 125-250*V, ac;		0.8A, 125V, DC;
	1/8hp, 125-250*V, ac.		0.4A, 250V, DC.
L127	10A, 125-250*-480Vac;	L131	10A, 1/4hp, 125-250*V, ac;
	1/4hp, 125Vac;		0.5A, 125V, DC;
	1/2hp, 250*Vac.		0.25A, 250V, DC;
L128	10A, 125-250*-480V, ac;		3A, 125V, ac "L".
	1/4hp, 125V, ac;	L135	5A, 1/8hp, 125-250*V, ac;
	1/2hp, 250*V, ac.		0.5A, 125V, DC;
	0.8A, 125Vdc;		0.25A, 250V, DC;
	0.4A, 250Vdc.		3A, 125V, ac "L".
L129	12A, 125-250*-480Vac;	L142	0.1A, 125V, ac.
	1/8hp, 125Vac;	L144	15A, 125-250*-480V, ac;
	1/4hp, 250*Vac;		1/2hp, 250V, ac;
	0.5A, 125Vdc;		1/4hp, 125V, ac;
	0.25A, 250Vdc.		0.25A, 250V, DC;
L130	5A, 125-250*-480V, ac;		0.5A, 125V, DC;
	1/10hp, 125V, ac;		2A, 600V, ac.
	1/6hp, 250V, ac.		
L145	20A, 125-250*-480V, ac;	L149	1A, 250*V, ac.
	10A, 125V, ac "L";	L150	5A, 250*Vac;
	0.5A, 125V, DC;		1A, 30Vdc.
	0.25A, 250V, DC;	L151	5A, 250Vac;
	1hp, 125V, ac;		5A, 30V, dc.
	2hp, 250*V, ac;	L156	11A, 1/3hp,
	2A, 600V, ac.		125-250*-277V, ac;
L147	15A, 125-250*-480Vac;		0.5A, 125V, DC;
	1/8hp, 125Vac;		0.25A, 250V, DC;

	1/4hp, 250*-277Vac.		4A, 125V, ac "L".
L148	15A, 125-250*-480Vac;	L157	10A, 1/3hp,
	1/8hp, 125Vac;		125-250*-277V, ac.
	1/4hp, 250*-277Vac;	L158	6A, 125-250*V, ac;
	0.5A, 125Vdc;		1/4hp, 125-250*V, ac.
	0.25A, 250Vdc.	L160	0.5A, 125V, DC.
L161	22A, 125-250*-480V, ac;	L169	10A, 125-250*-277V, ac;
	1/2hp, 125V, ac;		1/8hp, 125V, ac;
	1hp, 250*V, ac.		1/4hp, 250V, ac.
L162	5A, 125-250*-277V, ac;	L171	0.1A, 125V, ac;
	1/10hp, 250*V, ac.		0.1A, 30V, DC.
L163	3A, 125-250*-277V, ac;	L172	0.3A, 125V, DC;
	1/10hp, 250*V, ac.		5A, 250*V, ac.
L166	0.3A, 125V, DC.	L173	3A, 125V, ac;
L167	22A, 125-250*-277V, ac;		2A, 250*V, ac.
	3/4hp, 125V, ac;	L174	22A, 125-250*-480V, ac;
	1-1/2hp, 250*V, ac.		1/2hp, 125V, ac;
L168	10A, 125V, ac-DC;		1hp, 250*V, ac;
	1/4hp, 125V, ac-DC.		0.5A, 125V, DC;
			0.25A, 250V, DC.
L176	16A, 1/2hp 125-250*Vac;	L180	15A, 125-250*-480V, ac;
	5A, 125Vac "L".		2A, 600V, ac;
L178	20A, 125-250*-277V, ac;		1/4hp, 125V, ac;
	3/4hp, 125V, ac;		1/2hp, 250*V, ac;
	1-1/2hp, 250*V, ac.		1A, 125V, DC;
L179	20A, 125-250-277V, ac;		0.5A, 250V, DC.
	15A, 480V, ac;	L181	10A, 1/2hp,
	5A, 125V, ac "L"		125-250*-277V, ac.
	0.5A, 125V, DC;	L182	3A, 1/10hp, 125-250*V, ac.
	0.25A, 250V, DC;	L183	3A, 125Vac;

	1hp, 125V, ac;		10A, 1/3hp, 125Vac.
	2hp, 250*V, ac.	(L184)	1A, 125V, ac;
			1A, 30V, DC.
(L185)	4A, 250*V, ac;	L192	10A, 125-250*-277V, ac;
	1/10hp, 125V, ac.		1/4hp, 125V, ac;
L186	15.1A, 125-250*V, ac.		1/2hp, 250-277V, ac;
L189	11A, 125-250*-480V, ac;		3A, 125V, ac "L".
	1/8hp, 125V, ac;	L195	13A, 1/2hp, 125-250*V, ac;
	1/4hp, 250*V, ac.		0.5A, 125V, DC;
L190	11A, 125-250*V, ac;		0.25A, 250V, DC;
	5A, 30V, DC;		5A, 125V, ac "L".
	1/4hp, 125-250V, ac.	L197	15A, 125-250*-277V, ac;
L191	15A, 125-250*-277V, ac;		1/8hp, 125V, ac;
	1/2hp, 125V, ac;		1/4hp, 250*V, ac;
	1hp, 250*-277V, ac;		0.5A, 125V, DC;
	5A, 125V, ac "L".		0.25A, 250V, DC.
L200	3A, 125-250*-277V, ac;	L208	15A, 125-250*-480V, ac;
	1/10hp, 250V, ac;		1/2hp, 125V, ac;
	3A, 30V, DC.		1hp, 250*V, ac;
L201	10A, 1/4hp,		0.4A, 125V, DC;
	125-250*V, ac;		0.2A, 250V, DC.
	0.5A, 125V, DC;	L210	10A, 125V, ac-DC;
	0.25A, 250V, DC;		3A, 250*V, ac-DC;
	3A, 125V, ac "L";		1/4hp, 125V, ac-DC.
	3A, 30V, DC.	L212	11A, 125-250*V, ac;
L203	0.1A, 125V, ac-DC.		1/4hp, 125-250*V, ac;
L205	15A, 1/3hp,		5A, 30V, DC;
	125-250*V, ac.		0.5A, 125V, DC.
L206	7A, 125V, ac.		
L213	10A, 1/2hp,	L222	0.1A, 30V, DC.

	125-250*-277V, ac;	L223	6A, 125-250*V, ac;
	2A, 480V, ac.		2A, 30V, DC;
L214	10A, 1/3hp,		1A, 125V, ac "L";
	125-250*-277V, ac;		1/10hp, 125V, ac.
	2A, 480V, ac.	L224	20A, 125-250*-480V, ac;
L215	15.1A, 1/2hp,		0.5A, 125V, DC;
	125-250*-277V, ac;		0.25A, 250V, DC;
	0.5A, 125V, DC;		1hp, 125V, ac;
	0.25A, 250V, DC;		2hp, 250*V, ac.
	5A, 125V, ac "L".	L225	20A, 125-250*-277V, ac;
L216	10A, 1/3hp,		1hp, 125V, ac;
	125-250*-277V, ac;		2hp, 250*V, ac.
	0.5A, 125V, DC;	L226	5A, 125-250*V, ac.
	0.25A, 250V, DC;	L227	2A, 125V, ac.
	4A, 125V, ac "L".	L228	13A, 125-250*V, ac.
L229	0.1A, 125V, ac-DC;	L236	15.1A, 125V, ac.
			15.1A, 12UDC.
	1/10hp, 125V, ac.	L239	11A, 1/3hp,
			15.1A, 12UDC
L230	0.1A, 125V, ac-DC.		125-250*Vac.
L231	3A, 125-250*V, ac;	L242	16A, 1/2hp,
	1/10hp, 125-250*V, ac.		125-250*-277V, ac.
L232	11A, 125-250*-277V, ac;	L243	6A, 125V, ac;
	1/3hp, 125-250*-277V, ac;		4A, 250*V, ac;
	0.5A, 125V, DC;		2A, 30V, DC;
	0.25A, 250V, DC.		1A, 125V, ac "L";
L233	12A, 125-250*-480V, ac;		1/10hp, 125V, ac.
	1/4hp, 125V, ac;	L244	1A, 125V, ac;
	1/2hp, 250V, ac.		1A, 28V, DC.
L234	11A, 250*V, ac.	L248	13A, 1/10hp,



L235	N.C:5A, 125V, ac;		125-250*V, ac.
	N.O:15.1A, 125V, ac.		
L249	5A, 277V, ac	L259	15.1A, 250*V, ac
L250	15.1A, 1/2hp,	L260	10A, 277V, ac
	125-250*V, ac	L263	10A, 1/2hp,
L251	0.1A, 30V, dc		125-250*-277V, ac,
L254	5A, 250V, ac,		2A, 24V, dc
	0.5A, 125V, dc	L264	15.1A, 125-250*-277V, ac
L255	0.5A, 30V, dc	L265	10A, 125V, ac;
L256	16A, 125V, ac,		5A, 250*V, ac
	10A, 250*V, ac,	L267	5A, 28V, dc
	1/2hp, 125V, ac	L268	22A, 125-250*-480V, ac;
L258	5A, 250*V, ac,		0.5A, 125V, dc;
	5A, 125V, ac "L"		0.25A, 250V, dc
L272	20A, 125, 250*, 480 ac;	L285	10A, 1/6hp;
	10A, 125V, ac "L";		125-250V, ac
	1hp 125V, ac;	L291	11A, 1/3hp, 125,
	2hp 250*V, ac;		250* or 277V, ac;
	1/2A 125V, dc;		1/2A, 125V, dc;
	1/4A 250V, dc		1/4A, 250V, dc;
L277	1A, 125V, ac;		6A, 30V, dc;
	5A, 28V, dc		4A, 125V, ac "L"
L278	6A, 1/8hp;	L292	19A, 125-250-277V, ac;
	125-250*-277V, ac		1hp 125V, ac;
L279	1A, 125V, ac;		2hp, 250-277V, ac
	0.1A, 30V, dc		
L301	10A, 1/2hp;	L304	5A, 30 V, dc
	125-250V, ac	L305	2A, 1/6hp, 250V, ac;
	4A, 125V, ac "L"		3A, 1/10hp, 125V, ac
L303	22A, 125-250-277V, ac;	L311	10A, 277V, ac, 20A, 125V, ac

